



LTECH USB-DMX controller LT512



LT-512

Input Voltage	5V DC
Power Consumption	<2W
Connection	Mini USB
Internal Memory	120 steps
Channel Output Connector	512 XLR-3
Transmission Signal	DMX512
PC Software	LTECH LED player
Working Temperature	-30°C~65°C
Package Size	L140×W200×H52mm
Weight(G.W.)	330g

Auto Generated Effects
Creates some effect buttons and curves for each new show.

Groups + Sub-Groups
Easy and full feature selection.

Multiple Tabs + buttons
It is possible to create an unlimited number of tabs and buttons to organize your show and maximize your live performance impact.

DMX + MIDI external Controls
Triggers + controls via MIDI devices and DMX console.

Audio Triggers
Takes the Beat and level of music for scenes, steps, channels and faders.

Fading tool
For Theatre and Live: Fade In + Fade Out time + Delay + list of scenes.

XY + Color Effect generator
Create various shape movements and color sequences easily.

Layer Mask
Change show DMX levels as all your scene rapidly with only 1 action.

Matrix + Pixel Mapping
Easy graphic configuration.

Art-Net output signal
Up to 328 Universes management maximum. Output signal from 1945 computer network card.

Timeline options
Play, Repeat, Cut, Jump to Marker, Auto Repeat project, Time Zoom and scrolling.

Marker points
Add Marker points anywhere in lines.

Audio and Video Timeline
Unlimited number of timelines for lighting + 1 Audio Line + 1 Video Line.
30 mn to 24h Timeline
30 minutes (live) with 1 DMX DMX connected, 24 Hours with a NET10 or NET12 card connected.

Scene Blocks
Easy and quick scene block creation with Auto the scene keywords.

Video Player
Play more kind of format, Stereo, Auto + camera included.

ART NET PRO
Mac OS
Windows

Lighting and Visual Control Solutions - Pro DMX

Entertainment, Live, Sound, Lights, Theater, DJ's

LTECH